

# Updating NCSP3, NCSP35, & NCSP3DCCT



- 1) Go to <https://in-command.net/>
- 2) Click on Control Systems at the top of the page, select iN•Command w/ **Global Connect**.
- 3) Scroll down until you see **Resources**. Click on **Software Updates**. Click on **Display Commander OS & Body Control Module**. Download both files one at a time, **do not** place the files within folders, and **do not** unzip the zipped DC OS file. iN•Command display can only read the .zip file. Move the downloads to a USB flash drive - please only use drives **16GB or smaller**.
- 4) Insert the USB flash drive into the bottom of your iN•Command display.
- 5) On the iN•Command display, tap **Settings**.
- 6) Tap the **Down Arrow** and tap **Software**.
- 7) You should see the **DC & BCM Version**. One at a time tap each one, and tap **Update**.

DC Version file will explicitly be **NCSP3-DC V2.8.69.zip**

BCM Version file will explicitly be **ncspbcmv1.07.91.bin**

When downloading a file multiple times you may see a file renamed as **ncspbcmv1.07.91(1).bin**

The **(1)** will not allow iN•Command to read the file

Note that the “App Version” will be updated alongside the “DC Version” when applying “DC Version” update.

Current DC Version: **2.8.69** Current DC App Version: **2.3.187** Current BCM Version: **1.7.91**

